



MOT-602000BLDC-MB 60 Volt 2000 Watt Brushless DC Motor

Operating Voltage: 60 Volts DC
 Rated Power: 2000 Watts
 RPM: 5600
 Phase Wires: 3 (Yellow, Green, Blue)
 Phase Wire Terminals: 5.3mm ID Ring Terminals
 Sensor Wires: 5 (Red, Black, Yellow, Green, Blue)
 Sensor Wire Terminals: 2.8mm Wide Male Terminals

<p>Motor Phase Wires</p>		<p> Yellow to Yellow Controller Phase U Wire Green to Green Controller Phase V Wire Blue to Blue Controller Phase W Wire </p>
<p>Motor Sensor Wires</p>		<p> Red to Red Controller Sensor Wire +5V Black to Black Controller Sensor Wire GND Yellow to Yellow Controller Sensor U Wire Green to Green Controller Sensor V Wire Blue to Blue Controller Sensor W Wire </p>

