

MOT-602000BLDC 60 Volt 2000 Watt Brushless DC Motor

Operating Voltage: 60 Volts DC

Rated Power: 2000 Watts



RPM: 5600

Phase Wires: 3 (Yellow, Green, Blue)

Phase Wire Terminals: 5.3mm ID Ring Terminals

Sensor Wires: 5 (Red, Black, Yellow, Green, Blue)

Sensor Wire Terminals: 2.8mm Wide Male Terminals

Motor Phase Wires		Yellow to Yellow Controller Phase U Wire Green to Green Controller Phase V Wire Blue to Blue Controller Phase W Wire
Motor Sensor Wires		Red to Red Controller Sensor Wire +5V Black to Black Controller Sensor Wire GND Yellow to Yellow Controller Sensor U Wire Green to Green Controller Sensor V Wire Blue to Blue Controller Sensor W Wire

